

SE 50Hz Conventional Battery Charger

Model	Ah Battery	
	10 ÷ 12 h	Mains
24V/60A	360 ÷ 390	230/400
24V/80A	480 ÷ 520	230/400
24V/100A	600 ÷ 650	230/400
24V/120A	720 ÷ 780	230/400
24V/140A	840 ÷ 910	230/400
24V/160A	960 ÷ 1040	230/400
24V/180A	1080 ÷ 1170	230/400

36V/60A	360 ÷ 390	230/400
36V/80A	480 ÷ 520	230/400
36V/100A	600 ÷ 650	230/400
36V/120A	720 ÷ 780	230/400
36V/140A	840 ÷ 910	230/400
36V/160A	960 ÷ 1040	230/400

48V/50A	300 ÷ 325	230/400
48V/60A	300 ÷ 390	230/400
48V/80A	480 ÷ 520	230/400
48V/100A	600 ÷ 650	230/400
48V/120A	720 ÷ 780	230/400
48V/140A	840 ÷ 910	230/400
48V/160A	960 ÷ 1040	230/400

72V/60A	360 ÷ 390	230/400
72V/80A	480 ÷ 520	230/400
72V/100A	600 ÷ 650	230/400
72V/120A	720 ÷ 780	230/400
72V/140A	840 ÷ 910	230/400

80V/60A	360 ÷ 390	230/400
80V/80A	480 ÷ 520	230/400
80V/100A	600 ÷ 650	230/400
80V/120A	720 ÷ 780	230/400
80V/140A	840 ÷ 910	230/400